

Physics of Failure

9 Nov 2005

ISHEM 2005

NAPA Valley, CA




K. V. Jata and T.A. Parthasarathy

Metals, Ceramics and NDE Division

Wright Patterson Air Force Base Ohio




Concept





This talk 'Physics of Failure'





Failure Modes - Metals



Deformation	Yield	athermal plasticity	f (stress)
	Creep	thermally activated plasticity	f (temp, time, stress)
Fracture	Static	athermal / acyclic fracture	f (stress)
	Creep rupture	thermally activated cavitation leading to fracture	f (temp, time, stress)
	Dynamic fatigue	Cyclic plasticity leading to nucleation/growth of cracks	f (cyclic stress, cycle#)
Material Loss	Corrosion	athermal loss of material	f (time, environment)
	Oxidation	thermally activated	f (time, temp, O ₂ pres)




Metal Yield - factors



grain size


$$\sigma = \sigma_0 + \frac{k}{\sqrt{d}}$$



nano-copper, Morita

grain chemistry

$$\tau(\gamma) = \tau_o(\gamma) + (k1/T)^{k2} \left[\sum_{\text{allsolutes}} (\delta\tau / \partial C_{\text{solute},\gamma}^{0.5}) C_{\text{solute},\gamma}^{0.5} \right]$$





deformation history

$$\sigma = k\varepsilon^m$$


second phase
size, morphology
& distribution

$$\sigma \sim V_f^{1/2}, (1/a^n)$$






Metal Creep - factors




second phase size, morphology & distribution




$$\dot{\epsilon} \propto \frac{\sigma}{d^2}$$

grain size







Metal Static Fracture-Factors



- Strengthening phases
 - Coherent
 - Incoherent
- Grain boundary precipitates
- Second phase particles
- Grain size
- Impurities








Metal Fatigue - factors



Increase in grain size and particle spacing leads to increase in fatigue threshold stress intensity






Metal Fatigue - factors



Aluminum, steel, amorphous and crystallized glass
Growth rates scale range of crack tip opening displacements




$$da/dN = \Delta K^m \text{ ----(1)}$$

$$\Delta\delta = \beta(\Delta K^2 / \sigma_y * E) \text{ ----(2)}$$



Metal Fatigue - factors





Crack deflections increase with increase in grain size leading to better fatigue crack growth resistance.

Nan crystalline nickel has poor or faster fatigue crack growth rates





Metal oxidation - factors



P_{oxygen} of environment

Phase Fraction







Metal Corrosion - factors




Corrosion Fatigue



Frequency effects/ time to exposure
Grain size, microstructure, K_{1scc}



Corrosion Fatigue



Extremely Good Vacuum

Alloy Chemistry



Mode of failure - CMCs



Deformation	Yield	NONE	
	Creep	thermally activated plasticity (same as in metals)	f (temp, time, stress)
Fracture	Static	damage progression	f (stress)
	Creep rupture	fiber dominated	f (temp, time, stress)
	Dynamic fatigue	interface degradation	f (cycles, stress)
Material Loss	Corrosion	NONE	
	Oxidation	in non-oxides (same as in metals)	f (time, temp, O ₂ pres, H ₂ O)



Modes of failure - CMCs



Deformation	Yield	NONE	
	Creep	thermally activated plasticity (same as in metals)	f (temp, time, stress)
Fracture	Static	damage progression	f (stress)
	Creep rupture	fiber dominated	f (temp, time, stress)
	Dynamic fatigue	interface degradation	f (cycles, stress)
Material Loss	Corrosion	NONE	
	Oxidation	in non-oxides (same as in metals)	f (time, temp, O ₂ pres, H ₂ O)






Idealized Composite Behavior



Optimum composite properties require uncorrelated fiber fracture and decoupling from matrix during loading

Engineer fiber/matrix “interface” to promote debonding and sliding of fibers \Rightarrow fiber coatings








Dense Matrix Composites: RT Mechanical Behavior





Damage Progression in Tension - 2D SiC/CVI SiC Composites:



1. Initiate at macropores

2. Cracking of 90° tows

3. Microcracking of . . .




3. . . . 0° tows with progressive load transfer to fibers



Dense Matrix Composites: RT Mechanical Behavior



Modulus decreases with matrix damage:






Porous Matrix Composites: RT Mechanical Behavior




RT Tensile Behavior of Model Porous Matrix Composite:

**0°/90°: Fiber-dominated
behavior up to failure**



**±45°: Matrix-dominated
behavior up to failure**




L. Zawada et al, *J. Am. Ceram. Soc.*, 86, 981 (2003)




Porous Matrix Composites: HT Mechanical Behavior (cont'd)



Creep rupture and HT fatigue of COI N610/AS:



**Creep rupture dictated by creep rate of N610 fibers
(poor behavior highlights need for improved oxide fibers!)**




High fatigue limit due to absence of environmentally sensitive “interface”



Porous Matrix Composites: Fatigue Behavior




COI N610/AS:



**Stress-strain hysteresis provides
measure of fiber debonding/sliding**

***Interface Degradation a
measure of remaining life ?***



**Modulus change provides measure
of matrix microcracking**

***Modulus is a measure of
remaining life ?***






Porous Matrix Composites: Damage Progression in Service



**Sintering of porous matrix during
extended thermal exposure:**

COI N610/AS




**Matrix becomes stronger,
bonds strongly to fiber**




Porous Matrix Composites: Damage Progression in Service



Sintering of porous matrix during extended thermal exposure:



“Non-sintering” matrix:
Refractory mullite bonded with
small sintering particles (alumina)



Retained tensile strength
following HT aging (1000 h)




Pervasive CMC Behavior: Anisotropy of mechanical properties




Plagues all CMC's, worse for porous matrices:

COI N610/AS:

off-axis strength



interlaminar shear strength



CMC failures dominated by anisotropy:

Transverse thermal gradients cause delaminations

Accelerated creep in off-axis directions



SUMMARY

**Challenge: Connection of Physics of Failure
to Damage sensing at Material Level**



- (1) How do you take into consideration material factors that control physics of failure to devise new sensors?**
- (2) What scale of defect detection is important ?**
- (3) How does one handle when components become geometrically more complex and multi-materials are used?**
 - Constituent volume fractions, properties, processing defects expected to vary within component**
- (4) Meaningful damage must be detected against background of processing defects, etc.**
- (5) Physics of failure in operational-extreme environments not well documented !!**